

Sharing the printer on a network

Driver, utility file, and front panel interactions

If your Phaser 540 printer is shared by other users on a network, using the downloadable utility files or the printer's front panel to change the printer's default color correction setting can affect prints made by other users.

- When you print from a Tektronix driver with any TekColor color correction option *except Use Printer Setting*, the driver selection *overrides* the following selections *for prints made from the driver*:
 - A color correction utility file, if one has been downloaded to the printer.
 - The selection on the printer's front panel **TekColor Corrections** menu.
- When you print from a Tektronix driver using the **Use Printer Setting** option, your images are printed with one of the following selections:
 - A color correction utility file, if one has been downloaded to the printer.
 - The selection on the printer's front panel **TekColor Corrections** menu.
- When you print from a non-Tektronix driver, your images are printed with one of the following selections:
 - A color correction utility file, if one has been downloaded to the printer.
 - The selection on the printer's front panel **TekColor Corrections** menu.
- If the colors on your prints are not what you expected, and your system administrator has disabled some of the printer's front panel menus, ask them what settings are in effect and whether a color correction utility file has been downloaded to the printer.

LaserWriter Utility does not work

The *LaserWriter Utility* cannot be used if the printer is connected to a print server. See your system administrator to temporarily remove the printer from the print server to download any of the PostScript utility files.

Programs crashing on a network (Macintosh)

On Macintosh computers with a 68040 microprocessor (Quadra, Centris, and Performa 470 series), some programs may quit unexpectedly, or freeze the computer, when you try to open them over a network. To fix this problem, install the **Network Launch Fix** from the *AppleTalk Installer for the Macintosh* diskette shipped with your printer.

1. Insert the *AppleTalk Installer for the Macintosh* diskette into your computer's disk drive.
2. Drag the **Network Launch Fix** icon from the diskette to the *Extensions* folder, inside the *System Folder* on your computer's hard disk.
3. **Restart** your computer.