

Setting up the Adobe PostScript driver for Windows 95

NOTE



The files for this driver are available only on the printer's CD-ROM. If you already have the driver installed and you are only adding a printer, such as the Phaser 350 printer, open the Control Panel, double-click the Adobe driver icon, then continue with Step 7.

- 1** Insert the printer's CD-ROM into your CD-ROM drive.
- 2** Click the **Start** icon in the taskbar on your screen. In the menu that appears, click **Run**.
- 3** In the **Run** window, type in the drive the CD-ROM is in, followed by the `\ADOBEPS4` directory and the file name `SETUP.EXE` and click **OK**. For example:

C:\ADOBEPS4\SETUP
- 4** When the **AdobePS4 PostScript Printer Driver Setup** dialog box appears, click the **Read** button if you wish to see a text file with driver instructions. Click **Next** to continue, or **Exit** to quit.

- 5 In the **Install Setup Program** dialog box, decide if you want to copy the Adobe driver setup program to your hard disk, then click **Next**.

If you selected **Yes**, continue with the on-screen instructions.

- 6 In the **Printer Type** dialog box, select your printer's connection:
- Select **Local Printer** if your printer is connected directly to your computer, then click **Next**.
 - Select **Network Printer** if you are accessing your printer through a network. Click **Browse** to search the network and select a printer queue. Then click **Next**.

- 7 In the **Install PostScript Printer from PPD** dialog box, select the directory and drive for the printer's CD-ROM and the *ADOBEPS4* directory. Select your printer, then click **Next**.
- Select **Tektronix Phaser 350** if you have the standard version of the printer.
 - Select **Tektronix Phaser 350 600x300** if you have the printer's Extended Features option.

N O T E



If you are not sure which configuration of the printer you have, the printer's startup page lists this information under **Extended Features: Yes/No**.

- 8 In the **Local Port Selection** dialog box, select the port you want to use, then click **Next**. (You can configure the port in this dialog box at any time.)
- 9 In the **Add Printer** dialog box, type in the printer's name, select the printer as default, and decide if you want to print a test page. Click **Next** to continue.
- 10 If you see the **Different Versions Detected** dialog box, click **Next** to update the files from the printer's CD-ROM.

- 11 When the installation is finished, the **Tektronix Phaser 350 Properties** dialog box appears. Make selections in the driver, referring to Chapter 3 for more information on printer options.

N O T E



Refer to the Adobe PostScript Printer Driver User Guide on the printer's CD-ROM (USRGUIDE.PDF) for more detailed information on the AdobePS 4 driver.