

Setting up the Microsoft PostScript driver for Windows 95

- 1 Use either the printer's CD-ROM or diskette:
 - **CD-ROM:** Insert the printer's CD-ROM into your CD-ROM drive.
 - **Diskette:** Insert the Printer Software for Windows diskette into your disk drive.
- 2 Click the **Start** icon in the taskbar on your screen. In the menu that appears, click **Settings**.
- 3 In the menu that appears, click **Printers**; the **Printers** window appears.
- 4 In the **Printers** window, double -click **Add Printer**.
- 5 When the **Add Printer Wizard** window appears, click **Next**.

- 6 Select your printer's connection:
- Select **Local Printer** if your printer is connected directly to your computer, then click **Next**.
 - Select **Network Printer** if you are accessing your printer through a network. Click **Browse** to search the network and select a printer queue. Then click **Next**.
- 7 In the window listing **Manufacturers/Printers**, click the **Have Disk** button.
- 8 In the **Install From Disk** dialog box, do one of the following:

CD-ROM:

- a Click **Browse**.
- b In the **Open** dialog box select the **Drive** for the printer's CD-ROM.
- c Select the `\\WIN95_NT` directory under **Folders**.
- d Click **OK**.

Diskette:

- a** Click **Browse**.
 - b** In the **Open** dialog box select the **Drive** for the Printer Software for Windows diskette.
 - c** Click **OK**.
- 9** A list of Tektronix printers appears. Select your printer in the list, then click **Next**.
- Select **Tektronix Phaser 350** if you have the standard version of the printer.
 - Select **Tektronix Phaser 350 600x300** if you have the printer's Extended Features option.

N O T E



If you are not sure which configuration of the printer you have, the printer's startup page lists this information under **Extended Features: Yes/No**.

- 10 Select the port your printer is connected to, then click **Next**.
- 11 It is recommended that you use the default printer name shown under **Printer name**. Click **Yes** if you want this printer to be the default printer. Then click **Next**.
- 12 At the prompt, Would you like to print a test page? click **Yes** to verify the printer's connection, or click **No**. Then click **Finish**.

A status bar appears while files are copied to your computer.

- 13 If prompted, select the path for the PostScript driver files; these should be in your *WINDOWS/SYSTEM* directory.

If the files aren't installed on your hard disk, do *one* of the following:

- Select the drive for the printer's CD-ROM and the *WIN95_NT* directory, and click **OK**.
- Select the drive for the printer's diskette and click **OK**.

The software you need is installed.

14 If your printer is set up correctly, and you clicked **Yes** in Step 12, a test page prints showing the Windows 95 logo and information on your printer.

Your Phaser 350 printer is added to the **Printers** window.