

Removing a Windows 3.1 driver in Windows 95

If you installed a Tektronix Windows 3.1 printer driver in Windows 3.1, then upgraded from Windows 3.1 to Windows 95, the driver will appear in Windows 95. You should remove any Windows 3.1 drivers and install the Windows 95 driver and your printer.

Removing printers and older drivers

1. Start Windows 95.
2. Click the **Start** icon in the taskbar on your screen; a menu appears.
3. Move the cursor over **Settings**; another menu appears.
4. In the menu, click **Printers**; the **Printers** window appears.
5. Look for any Tektronix Phaser printers with **(TekColor)** as part of the printer's name.

Note *If you renamed your printer and **(TekColor)** is not part of the printer's name, but you think a Tektronix Phaser printer icon is an older printer file, move the cursor over the printer icon, and click the right mouse button. In the menu that appears, click **Properties**; the **Properties** dialog box appears. If **General** and **Details** are the only tabs available, then this is an older printer file. Continue with the steps below to remove the printer.*

6. Move the cursor over a printer icon, and click the *right* mouse button; a menu appears.
7. In the menu, click **Delete**. When prompted, click **Yes** to delete the printer files. If you are prompted to delete other software files associated with the printer, click **Yes**.
8. The printer's icon should now be removed from the **Printers** window.
9. Repeat Steps 6 and 7 for all Tektronix printers you have installed.
10. You can use the instructions in the "Adding the Phaser 550 printer to the Windows 95 driver" PDF file to reinstall any Tektronix printers for Windows 95.